

This purifier displays VOC ppm in real time and indicates which functions or modes are operational...

- 1) **V-Chip Mode**—Press to turn on Active Child LOCK. Press for three seconds to release child lock, or power off and restart.
- 2) **Color**—Press to cycle display colors from red, dark blue, dark green, purple, light blue, light green, then white.
- 3) **Filter**—Turns on at 2,000 hrs indicating Maintenance Required. After cleaning filter (by vacuuming) or replacing with a new filter (annually) press button for five seconds to reset.
- 4) **Shutoff**—Cycles shut-down time from 1 hour - 24 hours. Display will indicate when the unit will shut down.
- 5) **Speed**—Press to choose speed from low (1) to high (5).
- 6) **Power**—Cycles through total power-down and power-on. When first turned on, default setting is in “auto” mode.
- 7) **UV LED**—Operates sanitization function using germicidal wavelength LED and photo-catalytic oxidation (PCO); toggle on or off.
- 8) **Ions**—Operates multi-cluster ionization feature using DBI; toggle on or off. May also be used as sanitization function.
- 9) **Auto/Manual**—Adjusts machine to “auto” allowing the machine to operate based on the VOC sensor and pollution levels.
- 10) **Sleep**—Turns the display panel off, but keeps unit running. Press any key to return to “display on.”



KHAOS



WIFI App

- 1) DOWNLOAD the tuyu App from Google Play Store or Apple Store
- 2) CREATE an account with your email address and password.
- 3) CONNECT the app to the device. Press Fan Button for 3 seconds



warranty.bestlivingsystems.com

- 1) Your purchase MUST be registered on this website to take advantage of the 1-year manufacturer warranty.
- 2) You may purchase replacement parts directly from your seller. See below for instructions on maintaining your new KHAOS.

HEPA Filter



HEPA Filter should be cleaned (by vacuuming) at six months or when "FILTER" light illuminates. Replace annually.



To reinstall the HEPA filter after maintenance, twist the bottom of the unit to remove the cover, remove the existing filter and seat the new filter in its place. Return cover.

DBI Cell



DBI Cell should be replaced every three years or when the LED fails to illuminate. In highly contaminated environments, the cell screen may be removed and soaked in alcohol.

To install the DBI Cell, twist the bottom of the unit to remove the cover and identify the black socket at the top of the unit, attached to the fan grill. Push and twist the DBI Cell in place until it clicks and locks in place.

